



Mobile Media Solutions

INE-S900R Software Upgrade

Service Pack 2



ALPINE ELECTRONICS GmbH
Wilhelm-Wagenfeld-Straße 1-3,
80807 München, Germany
Phone 089-32 42 640

ALPINE ELECTRONICS OF U.K., LTD.
Alpine House
Fletchamstead Highway, Coventry CV4 9TW, U.K.
Phone 0870-33 33 763

ALPINE ELECTRONICS FRANCE S.A.R.L.
(RCS PONTOISE B 338 101 280)
98, Rue de la Belle Etoile, Z.I. Paris Nord II,
B.P. 50016, 95945 Roissy Charles De Gaulle
Cedex, France
Phone 01-48638989

ALPINE ITALIA S.p.A.
Viale C. Colombo 8, 20090 Trezzano
Sul Naviglio (MI), Italy
Phone 02-484781

ALPINE ELECTRONICS DE ESPAÑA, S.A.
Portal de Gamarra 36, Pabellón, Pabellón, 32
01013 Vitoria (Alava)-APDO 133, Spain
Phone 945-283588

Introduction

This guidebook describes the procedure for updating the INE-S900R software.

Requirements

- High Speed Internet connection
- PC including a CD writer
- Empty CD-Rom (2 pieces)

Software Improvements

- USB video playback
- Video playback on side screen
- USB audio file management – tree structure on audio search list
- SCDB with directional data encryption – if the Map Version of your device is 1.00, the pre-installed SCDB data will have to be updated
- Graphic User Interface change for postcode search
- DVD mechanism firmware update
- Navigation application software improvements



Software Upgrade for INE-S900R

1. Download the file "INE-S900R_Service-Pack-2.zip" to your PC and extract it. Insert an empty CD-R (CD-R 01).
2. Open your CD writer program. Go to "Copy Mode" and select "Burn Image". Browse for the file "01 - DVD Drive Software", add it and burn the CD-R (CD-R 01).
3. Insert an empty CD-R (CD-R 02). Open your CD writer program. Go to "Copy Mode" and select "Burn Image". Browse for the file "02 - Program Update", add it and burn the CD-R (CD-R 02).
4. Power on INE-S900R and insert the CD-R 01.
5. The update process will start. Confirm by clicking "Yes".



Note: Do NOT switch off ACC and do NOT eject the CD-R until the Update process is finished. The system reboots automatically after approximately 5 minutes (CD-R 01) and after 10 minutes (CD-R 02).

6. Repeat with step 4. using CD-R 02.

Version Information

Application Version 2.00